

Rx1 DIN /Data Receiver

Receiver for Wall Mounted and Hand-held Radio Transmitters

cue



Main Features

- Receiver for Tx Time, Tx Element and Tx Pocket transmitter
- Fully compatible with all CUE's controllers
- RS-232 port for connection to ipCUE controllers
- Unified enclosure designed for DIN rail installation
- Easy installation
- Small dimensions

Description

The Rx1 DIN /Data is a receiver designed for mounting in switchboards, which are equipped with DIN rail. It is a complete receiver, which is equipped with inputs for antenna or for external receiver Rx Ext. The receiver can be connected to a controller using bi-directional RS-232 communication port and standard driver.

Specifications

Wireless communication

- Radio frequency 433.92 MHz
- Number of codes 224

Wired communication

- RS-232, DB-9-female connector

Power supply

- 230 VAC / 50 Hz, 4 W, terminals

Physical

- Plastic enclosure

- Protection IP20

Dimensions

- 53 x 90 x 58 mm / 2.1" x 3.5" x 2.3"

- 3 DIN modules 17.5 mm

- Weight 0.25 kg / 0.6 lb

Operating environment

- Temperature -10° to +55° C

- Humidity 10% to 90% non-condensing

Applications

- Complete residential home automation
- Complete building automation
- Commercial single-room and multi-room applications
- Reconstructions and later installations

Order Information

Product code CS0450

Available Accessories

External receiver Rx Ext, product code CS0319-401.

Box Contents

Rx1 DIN /Data Receiver

Serial cable for ipCUE connection

Warranty Conditions, CE Declaration, RoHS Declaration

Data Sheet

DISTRIBUIDOR EM PORTUGAL



R. Sá de Figueiredo 6 - C

2790-233 Carnaxide

Telef. (+351) 21 417 76 21 ♦ Fax. (+351) 21 030 00 31

Web: www.sislite.pt - email: geral.sislite@sislite.pt